\bigcirc

Knowledge Base > Handsets and Device Provisioning > Polycom Devices > Polycom Manual Configuration

Polycom Manual Configuration

Mike Johnstone - 2025-09-03 - Polycom Devices

Polycom Manual Configuration

Manual configuration

You can quickly configure a handset by supplying four simple pieces of information in 2.1 with all other steps being optional.

- Retrieve the handset IP address: Home (Button) > Settings > 4. Status > 2. Network > 1. TPC/IP.
- 2. Web UI: Enter IP address (eg 192.168.1.11) into your browser.
- 3. Settings > Lines (select Line).

Follow instructions from the image below

- 1. SIP Protocol: Enable.
- 2. Identification: Display Name, Address (must be full DID), Label (usually same as Display Name).
- 3. Authentication: User ID (full DID), Phone's password from your switchboard, Disable Credentials.
- 4. SIP Server 1: plus.2talk.com Expires 180

Line 1	
SIP Settings	
SIP Protocol 💿 Enable	O Disable
H.323 Settings	
Identification	
Display Name	MikeJ
Address	13106341780
Label	Mike
Туре	Private OShared
Third Party Name	
Number of Line Keys	1
Calls Per Line	24
Enable SRTP	🗨 Yes 🔿 No
Offer SRTP	🔾 Yes 🛛 💿 No
Require SRTP	🔵 Yes 🛛 💿 No
Server Auto Discovery (🖲 Enable 🗌 Disable
Authentication	
Use Login Credentials	Enable 💿 Disable
Domain	
User ID 1	3106341780
Password •	
Outbound Proxy	
SIP Server 1	
Special Interop	Standard 🗸 🕄
Address	plus.2talk.com
Port	5061
Transport	DNSnaptr 🗸
Expires (s)	180
Subscription Expires (s)	180
Register	● Yes ○ No
Retry Timeout (ms)	0
Retry Maximum Count	3

- Tags
 <u>Device</u>
 <u>Polycom</u>