



[Knowledge Base](#) > [Handsets and Device Provisioning](#) > [Polycom Devices](#) > [Polycom Manual Configuration](#)

Polycom Manual Configuration

Mike Johnstone - 2025-10-02 - [Polycom Devices](#)

Polycom Manual Configuration

Manual configuration

You can quickly configure a handset by supplying four simple pieces of information in 2.1 with all other steps being optional.

1. Retrieve the handset IP address: Home (Button) > Settings > 4. Status > 2. Network > 1. TPC/IP.
2. Web UI: Enter IP address (eg 192.168.1.11) into your browser.
3. Settings > Lines (select Line).

Follow instructions from the image below

1. SIP Protocol: Enable.
2. Identification: Display Name, Address (must be full DID), Label (usually same as Display Name).
3. Authentication: User ID (full DID), Phone's password from your switchboard, Disable Credentials.
4. SIP Server 1: call.sipcity.com.au - Expires 180

Line 1

SIP Settings

SIP Protocol ☒ Enable ☐ Disable

H.323 Settings

Identification

Display Name
Address
Label
Type ☒ Private ☐ Shared
Third Party Name
Number of Line Keys
Calls Per Line

Enable SRTP ☒ Yes ☐ No
Offer SRTP ☐ Yes ☒ No
Require SRTP ☐ Yes ☒ No
Server Auto Discovery ☒ Enable ☐ Disable

Authentication

Use Login Credentials ☐ Enable ☒ Disable
Domain
User ID
Password

Outbound Proxy

SIP Server 1

Special Interop
Address
Port
Transport
Expires (s)
Subscription Expires (s)
Register ☒ Yes ☐ No
Retry Timeout (ms)
Retry Maximum Count
Line Seize Timeout (s)

- Tags
- [Device](#)
- [Polycom](#)