



Knowledge Base > Handsets and Device Provisioning > Handsets > Cisco SPA - Configuring your phone

Cisco SPA - Configuring your phone

Mike Johnstone - 2024-10-24 - Handsets

Cisco SPA - Configuring your phone

Quick Guide to Cisco SPA

While Cisco don't support encryption for remote device configuration connecting the Cisco SPA to our service is straight forward.

Your browser does not support the video tag.

Cisco SPA Web UI

- Retrieve the phones IP address > select the Settings button (highlighted below)
- Network (9) >> Current IP | Copy the IP
- Advanced settings: in browser type `http://<address>/admin/advanced` (eg 192.168.1.168/admin/advanced) to access admin mode.

Ext tabs

All the main settings required to configure the Cisco SPA's are accessed

within the Ext tabs. Complete:

1. General | Line enable Yes / NO (enable to YES)

2. Proxy and Registration

- Proxy + Outbound Proxy: call.sipcity.com.au
- Register: **Yes**
- Reg Expires: **120**

3. Subscriber information

- Display Name: can be both a Human name / or phone number
- Auth ID: full phone number including country (eg 612)
- User IDf: ull phone number including country

Additional Extensions

If you are not registering any additional lines on the Cisco SPA set Ext2, Ext3, Ext4 to:

- Line Enable: **No**

Time Zones

1. Type IP into browser followed by /admin/advanced (eg 192.168.36.172/admin/advanced)
2. System | Optional Network Configuration | Primary NTP >> time.google.com

Daylight Saving Time rules

1. Type IP into browser followed by /admin/advanced (eg 192.168.36.172/admin/advanced)
2. Regional | Miscellaneous >>Daylight Saving Time
Rule: start=10/30/-7/2:0:0;end=4/1/7/2:0:0; save=1
3. Set time zone rule

Tags

Device

Handsets