



[Base de conocimiento](#) > [Handsets and Device Provisioning](#) > [Handsets](#) > [Cisco SPA - Configuring your phone](#)

## Cisco SPA - Configuring your phone

Mike Johnstone - 2024-10-25 - [Handsets](#)

## Cisco SPA - Configuring your phone

### Quick Guide to Cisco SPA

While Cisco don't support encryption for remote device configuration connecting the Cisco SPA to our service is straight forward.

Your browser does not support the video tag.

### Cisco SPA Web UI

- Retrieve the phones IP address > select the Settings button (highlighted below)
- Network (9) >> Current IP | Copy the IP
- Advanced settings: in browser type `http://<address>/admin/advanced` (eg `192.168.1.168/admin/advanced`) to access admin mode.



### Ext tabs

All the main settings required to configure the Cisco SPA's are accessed within the Ext tabs. Complete:

1. General | Line enable Yes / NO (enable to YES)
2. Proxy and Registration
  - Proxy + Outbound Proxy: [call.sipcity.com.au](http://call.sipcity.com.au)
  - Register: **Yes**
  - Reg Expires: **120**
3. Subscriber information
  - Display Name: can be both a Human name / or phone number
  - Auth ID: full phone number including country (eg 612)
  - User ID: full phone number including country

Not Secure 192.168.1.162/admin/advanced

Small Business  
cisco SPA504G Configuration Utility

User Login basic | advanced

Voice Call History Personal Directory Attendant Console Status

info System SIP Provisioning Regional Phone User Attendant Console

Ext 1 Ext 2 Ext 3 Ext 4

General

Line Enable: yes

Call Feature Settings

Blind Attn-Xfer Enable: no  
Message Waiting: yes  
Default Ring: 2  
Conference Bridge URL:  
Mailbox ID:  
Voice Mail Subscribe Interval: 86400  
CFWD Notify Serv: no  
User ID with Domain: no  
Auto Ans Page On Active Call: yes  
Call Park Monitor Enable: no

MOH Server:  
Auth Page: no  
Auth Page Realm:  
Auth Page Password:  
Voice Mail Server:  
State Agent:  
CFWD Notifier:  
Broadsoft ACD: no  
Feature Key Sync: no

Proxy and Registration

Proxy: call.sipcity.com.au  
Outbound Proxy: call.sipcity.com.au  
Alternate Proxy:  
Alternate Outbound Proxy:  
Use Outbound Proxy: no  
Register: yes  
Register Expires: 120  
Use DNS SRV: no  
Proxy Failback Invl: 3600  
Dual Registration: no

Use OB Proxy In Dialog: yes  
Make Call Without Reg: no  
Ans Call Without Reg: no  
DNS SRV Auto Prefix: no  
Proxy Redundancy Method: Normal

Subscriber Information

Display Name: 61289707510  
Password: \*\*\*\*\*  
Auth ID: 61289707510  
SRTP Private Key:  
Resident Online Number:

User ID: 61289707510  
Use Auth ID: yes  
Reversed Auth Realm:

SIP URI:

## Additional Extensions

If you are not registering any additional lines on the Cisco SPA set Ext2, Ext3, Ext4 to:

- Line Enable: **No**

## Time Zones

1. Type IP into browser followed by /admin/advanced (eg 192.168.36.172/admin/advanced)
2. System | Optional Network Configuration | Primary NTP >> [time.google.com](http://time.google.com)

## Daylight Saving Time rules

1. Type IP into browser followed by /admin/advanced (eg 192.168.36.172/admin/advanced)
2. Regional | Miscellaneous >> Daylight Saving Time  
Rule: start=10/30/-7/2:0:0;end=4/1/7/2:0:0; save=1
3. Set time zone rule

- Etiquetas
- [Device](#)
- [Handsets](#)