



## Grandstream - Manual setup

Mike Johnstone - 2024-10-27 - Handsets and Device Provisioning

# Grandstream - Configuring your phone

## Quick Guide to Grandstream

In addition to the Grandstream ATA 80x we now support Grandstreams latest GRP handsets via our device provisioning.

- Retrieve the phones IP address > select the Settings button (highlighted below)
- Status | Network Status | Ethernet | IPV4 address
- Advanced settings: in browser type <http://<address>> to access web admin mode.

### 1. General Setting

- Activate Account: **Enable**
- Account Name: **Can phone and owner name (eg Sally)**
- SIP user ID: **Phone number**
- SIP Auth ID: **Phone number**
- SIP server: **[call.sipcity.com.au](http://call.sipcity.com.au)**

### 2. SIP setting (tab)

- SIP Registration: **Enable**
- Subscribe Exp: **60**
- SIP Transport: **TLS**
- Local SIP port: **5061**

